

进入管理软件看到界面应该是这样的,此时阵列状态(status)有黄色感叹号了,提示 need attention



点击 logical,看到下图界面。阵列前面一个黄色的圈。Drives 下只有 1 块硬盘(由于测试,我只用了 2 块盘做的 RAID1),此时我已经把一块盘拔下,换上了 1 块新的盘,新的硬盘在 unconfigured drivers 下面,下面我们要做的就是对 RAID1 恢复,把新加的磁盘(unconfigured drivers)添加进阵列



≣ ∎egal	RAID Storage Manager - 9.00.0100								_ 8 ×
Manage	<u>G</u> o To <u>L</u> og <u>T</u> ools <u>H</u> elp								
	S 🕐 🛢 🕫 🕜								
								LSI	
Dashboar	rd Physical Logical			Wel	come: adm	inistrator [Full Access]]	L	og Off
user	-7f155ee327	Prop	erties						
WeedAll SAS STORM2 (Dus 8, Jav 0) WeedAll SAS STORM2 (Dus 8, Jav 0) WeedAll SAS STORM2 (Dus 8, Jav 0) Wirtual Drive(5): Wirtual Drive(5): Wirtual Drive(5), 464, 729 GB, : WeedAll Sas Stormatic Sto		Но	st Name			user-7f155ee327			
		GB, : IP	Address			192. 168. 0. 144			
		5.762 Op	erating System			Windows 2003			
	Backplane, Slot: 3, SATA, 931.5	I3 GB, OS	Version			5.2			
		os	Architecture			x86			
		1			n .				
10	Error Level Date / Time	Sussanful	l		Descrip	102 162 0 144 Acc	H.d.: Rull	Clinet Times	20
94	[Informat 2012-03-12, 14:12:16 [Tpformat 2012-03-12 14:11:26	Controller	rug on to the s	server User: administrator stablished since nower on:	, client: Time	2012-03-12 14:11:26	236 Seconds	Client lime:	20
93	[Informat 2012-03-12, 14:11:26	Controller	ID: O Time e	established since power on:	Time	2012-03-12, 14:11:26	83 Seconds		
92	[Critical 80seconds from reboot	Controller	ID: O VD is r	now DEGRADED VD O					-
Displayi	ng log from server								

如下图,在 unconfigured drivers 下面的磁盘上右击,选择 Replace missing disk,用这块没有 配置的硬盘取代丢失的硬盘

2





Controller ID: 0 Unexpected sense: FD = --:--:3 - Invalid field in CDB, CDB = 0x4d 0x00 0x4d 0x... Successful log on to the server User: administrator, Client: 192.168.0.144, Access Mode: Full, Client Time: 20... [Informat... 2012-03-12, 14:13:40 [Informat... 2012-03-12, 14:12:16

南京文禹信科技发展有限公司 地址:南京市珠江路 88 号新世界中心 B 座 2707 室 电话: 025-68891010 68891011 传真: 025-68858836



完成上一步之后,阵列卡还会继续报警,但 unconfigured drivers 下面的磁盘前面多了一个红色的圈,此时要刷新一下,如下图,点击 manage 下拉菜单下的 reflesh



刷新之后看到的是下图,此时本来在 unconfigured drivers 下面的磁盘已经移到 drive group 下的 drive 下面。此时新添加的磁盘前面有个红色的圈,是因为当前的硬盘状态为 Off line, 右击选中的磁盘点击 make disk online,到这里就完成了 RAID 的重建



Server - 0 00 0100										
Manage Go To Log Tools Help										
1 V 🗢 🔿 🛢 🕸 🕢										
EccaRATE Storage Hanager - 9.00.0100										
Manage <u>G</u> o To <u>L</u> og <u>T</u> ools <u>H</u> elp										
i 🗑 🔩 🕗 🚔 🐗 🚱										
			LS	2](3**						
Welcome: administrator [Full Access]										
Dashboard Physical Logical										
user-7f155ee327	Properties									
megankli SAS Glocimiz (pus 6, Dev 0) Group: 0, RAID 1 Group: Virtual Drive(s):	General :		Media Error Count	0						
	Usable Capacity	930.391 GB	Pred Fail Count	0						
Backplane, Slot: O, SATA, 465.762	Raw Capacity	931.513 GB	Enclosure Properties							
Make Drive Online	Product ID	WDCWD1003FBYX1	Enclosure ID	252						
Stop Locating Drive	Vendor ID	ATA	Enclosure Model	Backpla						
<u>M</u> ark Drive as Missing Start Rebuild	Device ID	9	Enclosure Location	Interna						
	Status	Offline	Connector	Int. Por						
	Drive Speed	3.0 Gbps	Slot Number	3						
	Negotiated Link Speed	3.0 Gbps	Drive Security Properties:							
	SCSI Device Type	Di sk	Full Disk Encryption capable	No						
	SAS Address O	0x73853723A6AA9394	Data Protection Properties:							
	Power Status	0n	Data Protection	Incapal 🚽						
				<u> </u>						
ID Error Level Date / Time		Description								
100 [Informat 2012-03-12, 14:15:50 Control 99 [Informat 2012-03-12, 14:15:08 Control	ller ID: O Unexpected sense: Pi ller ID: O Unexpected sense: Pi) =::3 - Invalid field i) =::3 - Invalid field i	n CDB, CDB = 0x4d 0x00 0x4 n CDB, CDB = 0x4d 0x00 0x4	d 0x▲						



南京文禹信科技发展有限公司 地址:南京市珠江路 88 号新世界中心 B 座 2707 室 电话: 025-68891010 68891011 传真: 025-68858836

5